

## Connector "A"

		3	4		5	6	7		8	9	10		
		14	15	16	17	18	19	20	21	22	23		24
		25	26		27	28	29				31		

1. EMPTY SLOT
2. EMPTY SLOT
3. 2WBS - EVAP Bypass Solenoid Valve  
wire color: blue
4. VSU - EVAP Control Canister Vent Shut Value  
wire color: light green / white
5. CRS - Cruise Control Signal  
wire color: blue / green
6. PCS - Evap Purge Control Solenoid Valve  
wire color: red / yellow
7. ATPD - A/T Gear Position Switch  
wire color: yellow
8. S02SHTC - Second O2 Sensor Heater Cntrl  
wire color: black / white
9. ATPNP - A/T Gear Position Switch  
wire color: light green
10. SCS - Service Check Signal  
wire color: brown
11. EMPTY SLOT
12. EMPTY SLOT
13. EMPTY SLOT
14. D4IND - A/T D4 Indicator  
wire color: green / black
15. EMPTY SLOT (Civic plug)  
FLR - Fuel Pump Relay (Integra plug)  
wire color: green / yellow
16. EMPTY SLOT (on Integra connector)  
FLR - Fuel Pump Relay (on Civic connector)  
wire color: green / yellow
17. ACC - A/C Clutch Relay  
wire color: black / red
18. MIL - Malfunction Indicator Light  
wire color: green / orange
19. NEP - Engine Speed Pulse  
wire color: blue
20. FANC - Radiator Fan Control  
wire color: green
21. K-Line - OBD2 Scan Tool Signal  
wire color: blue / yellow
22. ATP L - A/T Gear Position Switch  
wire color: blue
23. SNO2S - Secondary Heated O2 sensor 2  
wire color: white / red
24. STS - Starter Signal Switch  
wire color: blue / white
25. EMPTY SLOT
26. PPSW - P/S Power Switch Signal  
wire color: green
27. ACS - A/C Switch Signal  
wire color: blue / red
28. SLU - A/T brake related  
wire color: white / red
29. P TANK - Fuel Tank Pressure  
wire color: light green
30. EL (ELD) - Electrical Load Detector  
wire color: green / red
31. EMPTY SLOT
31. BKSU - Brake Switch  
wire color: green / white

## Connector "C"

1	2	3		5	6	7		8	9	10
				16	17	18	19	20	21	22
				26	27	28		29	30	31

1. P02SHTC - Primary O2 Sensor Heater Control  
wire color: black / white
2. ALTC - Alternator Control  
wire color: white / green
3. KS - Knock Sensor  
wire color: red / blue
4. EMPTY SLOT
5. ALTF - Alternator FR Signal  
wire color: white / red
6. EGRL - EGR Valve Lift Sensor  
wire color: white / black
7. SG1 - Sensor Ground (grnd for MAP)  
wire color: green / white
8. CKPP - CKP sensor P-side  
wire color: blue
9. CKPM - CKP sensor M-side  
wire color: white
10. VTM - VTEC Pressure Switch  
wire color: blue / black
11. EMPTY SLOT
12. EMPTY SLOT
13. EMPTY SLOT
14. EMPTY SLOT
15. EMPTY SLOT
16. PHO2S - Primary Heated O2, Sensor-1  
wire color: white
17. MAP - Manifold Absolute Pressure Sensor  
wire color: red / green

## Connector "B"

1	2		3	4	5		6	7	8
9	10	11	12	13		15	16	17	18
	20		21	22		23		25	

1. IGP1 - Power Source  
wire color: yellow / black
2. P61 Power Ground  
wire color: black
3. INJ2 - Injector 2  
wire color: red
4. INJ3 - Injector 3  
wire color: blue
5. INJ4 - Injector 4  
wire color: yellow
6. IACVP - IACV Positive Side (Civic Only)  
wire color: black / blue
7. ES (ESOL) - EGR Control Solenoid Valve  
wire color: red
8. LS-HLC LSM (CVT trans related)  
wire color: pink / black
9. IGP2 Power Source  
wire color: yellow / black
10. P62 Power Ground  
wire color: black
11. INJ1 - Injector 1  
wire color: black
12. VTS - VTEC Solenoid  
wire color: green / yellow
13. ICM - Ignition Control Module  
wire color: yellow / green
14. EMPTY SLOT  
wire color: green / red
15. IACVN - IACV Negative Side (Civic Only)  
wire color: orange
16. IAB - Intake Air Bypass Cntrl Sol. Valve (GSR Only)  
wire color: ??
17. LS+HLC LSM - A/T CVT Trans Related  
wire color: red (D16V7)  
wire color: grn/wht (D16V5)
18. SC LSM - CVT trans related  
wire color: pink / blue
19. EMPTY SLOT
20. LG1 - Logic Ground  
wire color: brown / black
21. VBU - Voltage Backup  
wire color: white / blue
22. LG2 - Logic Ground  
wire color: brown / black
23. IACV - Idle Air Control Valve  
wire color: black / blue
24. EMPTY SLOT
25. SC LSP - CVT trans related  
wire color: yellow

12V +  
Ground - Black

S = speed  
E & B  
+ Power

VSS  
Blue/white

18. S62 - Sensor Ground  
wire color: green / black
19. VCC1 - Sensor Voltage for MAP  
wire color: yellow / red
20. TDCP - TDC sensor P-side  
wire color: green
21. TDCM - TDC sensor M-side  
wire color: red
22. CKFP - CKF Sensor P-side  
wire color: blue / red
23. VSS - Vehicle Speed Sensor  
wire color: blue / white
24. EMPTY SLOT
25. IAT - Intake Air Temp  
wire color: red / yellow
26. ECT - Engine Coolant Temp Sensor  
wire color: red / white
27. TPS - Throttle Position Sensor  
wire color: red / black
28. VCC2 - Sensor Voltage  
wire color: yellow / blue
29. CVPP - CVP sensor P-side  
wire color: yellow
30. CYPM - CVP sensor M-side  
wire color: black
31. CKFM - CKF sensor M-side  
wire color: white / red